RW-1 Spirit Detector

Intro

The RW-1 utilizes the 180-degree scanning range, combined with the distance measurement can detect targets and spirits* and represent them on the screen with different colored dots depending on their range. Target trigger range is 1cm to 200cm's. The display screen provides intuitive visual feedback, allowing users to understand the distance information of the targets.

Setup and Use

The RW-1 is simple to use. Simply toggle the power switch to the desired position.

On Sound – Audio sound when targets are detected, Higher the tone closer the target has been detected.

On Silent – No audible sound, quiet mode. This setting is useful if you are in a small area where a wall or other objects could be in range of the RW-1.

Information

Color Range – Red < 25cm, Yellow < 50cm, Blue < 75cm, White < 100cm, Green < 126cm, Orange >126cm

Screen Display – **Deg**: Current sensor degree **CM**: Current target range,

Screen Hit Counter – Upper right corner displays total hit count for each range since RW-1 was turned on. Counter displays color code range for each hit.

Radar Area - 1 to 180 degrees radar with 6 ranges 25cm, 50cm, 75cm, 100cm, 120cm, over 120cms. Colored dots will be shown where target was detected. Orange dots at edge of radar target past 120cm.

*Note: While this unit is designed to detect potential anomalies, it is essential to acknowledge that there is no scientific evidence to conclusively prove its ability to detect spirits or paranormal activity. The results obtained through the use of this device are subjective and should be treated as theoretical.

Contact Us: ron@boosparanormal.com ©2024 – Boo's Paranormal Ver1.3